



DS200[®] Digital Precinct Scanner

EVS 6.0.5.0

Firmware 2.17.5.0

Poll Worker Guide



© 2020 by Election Systems & Software, 11208 John Galt Blvd., Omaha, NE 68137-2364

All rights reserved. Printed in the USA

This document, as well as the product described in it, is furnished under license and may be used or copied only in accordance with the terms of such license. The content of this document is furnished for informational use only, is subject to change without notice, and should not be construed as a commitment by Election Systems & Software, Inc. Election Systems & Software, Inc., assumes no responsibility or liability for any errors or inaccuracies that may appear in this document. Except as permitted by such license, no part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, recording, or otherwise, without the prior written permission of Election Systems & Software, Inc.

Disclaimer

Election Systems & Software does not extend any warranties by this document. All product information and material disclosure contained in this document is furnished subject to the terms and conditions of a purchase or lease agreement. The only warranties made by Election Systems & Software are contained in such agreements. You should ensure that the use of this equipment complies with all legal or other obligations of their governmental jurisdictions.

All products described in this document are registered trademarks of Election Systems & Software Inc. All other products mentioned are the sole property of their respective manufacturers.

Proprietary Information

ES&S has identified and appropriately marked relevant portions of this document, which it considers confidential and proprietary. We request confidential treatment by the EAC of such information and would expect that such information is exempt from required disclosure. In the event a third-party requests disclosure of information which ES&S considers confidential and proprietary, we would ask that the EAC notify ES&S of such requested disclosure in order to provide us with an opportunity to seek exemption from disclosure.

The document sections referenced below contain Election Systems and Software, Inc. (ES&S) confidential information, which is provided for the sole purpose of permitting the recipient, to evaluate the ES&S Voting System submitted herewith. The following sections are designated as "Proprietary and Confidential" by Election Systems & Software.

Table of Contents

DS200 Digital Precinct Scanner	5
Poll Worker Learning Plan.....	5
Learning Objectives	5
Agenda.....	5
DS200 Digital Precinct Scanner	6
Product Overview & Ballot Box Components	6
Digital Scanner Components.....	7
Preparing the DS200 for Use	8
DS200 Scanner Setup	8
Powering Up the Scanner.....	8
Preparing the Printer Tape	8
Opening the Polls for Voting.....	9
Opening the Poll	9
Printing the Zero Totals Report.....	9
Go to Voting Mode	9
Casting Ballots with the DS200	10
Inserting Ballot for Tabulation.....	10
Ballot Exceptions.....	10
Unreadable Marks on Ballots	10
End of Voting	11
Closing Polls & Printing Reports	11
Transmitting Results	11
Power Down Methods.....	11
Appendix A: Troubleshooting the DS200.....	12
DS200 Not Plugged Into Power Source	12
Reports Not Visible on Paper.....	12
Cleaning the DS200 Touch Screen & Scanner.....	12

THIS PAGE HAS BEEN LEFT INTENTIONALLY BLANK

DS200[®] Digital Precinct Scanner Poll Worker Learning Plan


Learning Objectives

This course will provide you with the skills to successfully use the DS200 in your jurisdiction. Upon completion of this course, you will be able to:

- Set up the DS200 for voting
- Assist voters in using the DS200


Agenda

- Understanding the DS200
- Using the DS200 for Voting
- Applying what you have learned



DS200[®] Digital Precinct Scanner

Product Overview & Ballot Box Components



The DS200 is a precinct-level tabulator that can also be used as a central count tabulator for voting over an extended period, as with early or absentee voting. Both one and two-sided ballots can be read by the DS200 to determine valid ballot marks and extraneous marks, such as smudges or folds. All election results are stored on an encrypted removable USB flash drive, which is used to transfer results to the Electionware Results module.

1 Clam shell carrying case

4 Main ballot bin

2 Ballot box base

5 Locking wheels

3 Auxiliary bin

Digital Scanner Components



1 Rear access compartment
(modem enclosed)

5 ExpressVote card feed

2 Front access compartment


6 Paper ballot feed

3 Thermal printer

7 Touch screen

4 Touch screen lock

Preparing the DS200 for Use




DS200 Scanner Setup

The DS200 uses two different keys: a standard silver key and a barrel key.

The silver key is used only for the ballot box, carrying case, and optional blue bin locks. The barrel key is used only for locks on the DS200 scanner. You will need both keys to open and start the DS200.

Open the front of the carrying case by using the silver ballot box key and unlatching the two front tabs.

More information: DS200 Operator's Guide, p. 53




Powering Up the Scanner

Using the barrel key, open the DS200 touch screen.

If the machine is plugged in to AC power, the scanner should automatically power on when the screen is lifted.

If the scanner does not automatically power on, use the barrel key to open the Front Access Compartment and press the Power button.

More information: DS200 Operator's Guide, p. 39



Preparing the Printer Tape

The DS200 contains an internal thermal printer for reports. To change a tape roll, open the Front Access Compartment and press the blue lever.


Replace the tape roll and pull the end of the paper out of the tape opening with the treated side facing the right side of the opening.

NOTE: Thermal treated side of paper will leave gray streak when scratched.

Hold the end of the tape roll while pressing firmly on the printer door to ensure it is locked.

More information: DS200 Operator's Guide, p. 81

Opening the Polls for Voting




Opening the Poll

Once the Election Definition is loaded and all Admin functions are completed you can open the poll.

Touch **Open Poll**.

Allow default reports to complete printing. If you need to print any additional Zero Totals Reports, proceed to the next section for instructions.

More information: *DS200 Operator's Guide*, p. 104




Printing the Zero Totals Report

The DS200 should be configured to automatically print at least one (1) Zero Totals Report when the poll opens.

Should you need to print additional copies, you must do so before going to voting mode.

Touch **Report Options** from the Open Poll screen and select the **Zero Totals Report**. Make sure the Report Format is set to **Public** and touch **Print Report**.

More information: *DS200 Operator's Guide*, p. 175



Go to Voting Mode


When you are ready to start scanning ballots for live voting, touch **Go To Voting Mode**.

Close and lock the Front Access Compartment using the barrel key.

Verify the Public Count at the top of the screen is at "0" before voting starts on the first day of tabulation or testing. This count will increase by one each time a ballot is cast.

More information: *DS200 Operator's Guide*, p. 106

Casting Ballots with the DS200




Inserting Ballot for Tabulation

You can scan both paper ballots and printed ExpressVote cards with the DS200.

When the DS200 is ready for ballots to be tabulated, the ballot insertion screen will appear, providing instructions on how to insert the ballot.

Ballots may be inserted in any orientation. Do not push the ballot too hard into the scanner; insert the leading edge into the scanner and allow it to grab and pull the ballot automatically.

More Information: DS200 Operator's Guide, p. 107




Ballot Exceptions

If your election is coded to prompt for ballot exceptions, a message may appear asking whether the voter wishes to cast their ballot as is, or return it for corrections. The following instances may prompt such a message:

- **Blank Ballots:** no voting marks detected
- **Undervoted Ballots:** fewer marks than allowed "Vote For" number
- **Overvoted Ballots:** more marks than allowed "Vote For" number

More Information: DS200 Operator's Guide, p. 112



Unreadable Marks on Ballots


An alert message indicating which contest(s) are impacted may appear if the ballot contains unreadable marks.

If the ballot is unreadable in its entirety (due to damage, markings, etc.), the DS200 will return the ballot automatically and begin beeping.

For any ballot automatically returned, read the error message on the screen before removing the ballot. Once the ballot is removed from the tray, the error message disappears.

More Information: DS200 Operator's Guide, p. 115

End of Voting




Closing Polls & Printing Reports

To close the poll at the end of voting, open the Front Access Compartment and push the **Close Poll** button. On the touch screen, touch **Close Poll** to end voting.

Allow the default reports to print. A confirmation screen appears indicating successful poll closure.

If any further report copies are needed, touch **Report Options** and print. Touch **Finished - Turn Off** if you are ready to power down the scanner.

More information: *DS200 Operator's Guide*, p. 129



Transmitting Results


If transmitting results manually, remove the Election Definition media after the DS200 powers down completely. Read the USB into ERM.

If transmitting results via modem, touch the **Admin** icon and enter the Administration Code. Touch **Accept**.

Touch **Transmission** and then touch **Send Results** to display the wireless signal strength. Touch **Begin Modem Process** to send results to ERM.

Touch **OK** to return to the Administration Menu.

More information: *DS200 Operator's Guide*, p. 143



Power Down Methods

During early voting, to power down with polls open, touch the **Tools** icon and enter the Election Code. Touch **Report Options** and select the **Admin** icon. Touch **Shutdown**.

At the end of Election Day voting, push the **Close Poll** button inside the Front Access Compartment to access the **Admin** menu and touch **Shutdown**.

If the polls are closed, you will be directed to the Voting Device Status screen where you can touch **Shutdown** to power down the scanner.

More information: *DS200 Operator's Guide*, p. 126

Appendix A: Troubleshooting the DS200

DS200 Not Plugged Into Power Source

PROBLEM: After turning on the DS200 the screen power icon on the top right of the screen shows the plug is not connected. What does this mean?

CAUSE: The DS200 is not plugged into the AC power cord or the wall outlet is defective.

SOLUTION: Ensure all power cords are plugged in securely.

REMINDER: there are two parts to the DS200 power supply; make sure the transformer is plugged into the cord.

Test all outlets using a night light or other small electrical device. If using a strip power cord (not recommended) assure the strip is turned on. Check DS200 power cord for damage. If damage is found, replace the cord.

Reports Not Visible on Paper

PROBLEM: The reports are generating, but no printing is visible on the paper. What's wrong?

CAUSE: The DS200 printer uses thermal paper and heat transfer to print the information. Printer functionality without visible print means the paper roll is inserted incorrectly, causing the printer to print to the untreated side of the tape roll.

SOLUTION: Open the Front Access Compartment and press the blue lever to open the printer door. Reinsert the paper roll with the treated side of the paper to the right side of the scanner. Reprint report(s) as necessary.

Cleaning the DS200 Touch Screen & Scanner

PROBLEM: What do I use to clean the exterior of the DS200 including the touch screen?

SOLUTION: The DS200 touch screen and exterior can be cleaned with isopropyl alcohol wipes or isopropyl alcohol on soft cloth. Do not spray or apply the isopropyl alcohol directly onto the touch screen or DS200 scanner

WARNING: Do not use products containing ammonia, such as Windex. This can cause the screen to become deteriorated over time. Use only isopropyl alcohol for cleaning the touch screen and scanner.

Use canned air to clear any paper dust from the scanner area, taking care to not tip the can upside down while spraying. Do not shake the can before using the canned air.

THIS PAGE HAS BEEN LEFT INTENTIONALLY BLANK

